

MLFB-Ordering data

6SE6440-2AD31-1CA1



Figure similar

Client order no. : Item no. :
Order no. : Consignment no. :
Offer no. : Project :
Remarks :

| Rated data | | General | General tech. specifications | |
|----------------------------------|---------------------|---------------------|------------------------------|--|
| Input | | Power factor λ | 0.95 | |
| Number of phases | 3 AC | Efficiency η | 0.96 | |
| Line voltage | 380 480 V ±10 % | Amb | Ambient conditions | |
| Line frequency | 47 63 Hz | Cooling | Fan | |
| Rated current (LO) | 33.80 A | Ambient temperature | | |
| Rated current (HO) | 23.10 A | Operation (LO) | -10 40 °C | |
| Output | | Operation (HO) | -10 50 °C | |
| Number of phases | 3 AC | Transport | -40 70 °C | |
| Rated voltage | 480 V | Storage | -40 70 °C | |
| Rated power (LO) | 15.00 kW / 20.00 hp | | | |
| Rated power (HO) | 11.00 kW / 15.00 hp | | | |
| Rated current (LO) | 32.00 A | | | |
| Rated current (HO) | 26.00 A | | | |
| Pulse frequency | 4000 Hz | | | |
| Output frequency for V/f control | 0 650 Hz | | | |

As a result of legal stipulations, a limit to 550 Hz is in production

Overload capability

Low Overload (LO)

140 % output current for 3 s, followed by 110 % output current for 57 s followed by 100 % output current for 240 s in a 300 s cycle time

High Overload (HO)

150 % output current for 60 s, followed by 100 % output current for 240 s in a 300 s cycle time



MLFB-Ordering data

6SE6440-2AD31-1CA1



Figure similar

| Mechanical data | | Co | Connections | |
|-------------------------|----------|-------------------------|-----------------------|--|
| Degree of protection | IP20 | Motor end | | |
| Size | FSC | Conductor cross-section | 10.00 mm ² | |
| Net weight | 5.70 kg | | | |
| Width | 185.0 mm | | | |
| Height | 245.0 mm | | | |
| Depth | 195.0 mm | | | |
| Inputs / outputs | | | | |
| Standard digital inputs | | | | |
| Number | 6 | | | |
| Relay output | | | | |
| Number | 3 | | | |
| Analog inputs | | | | |
| Number | 2 | | | |
| Analog outputs | | | | |
| Number | 2 | | | |
| PTC/ KTY interface | | | | |
| Number | 1 | | | |